

B-900-MoIP SYSTEM C4 SETUP Rev:181211-0925

C4 CONTROLLER SETUP

CONTACTING TECH SUPPORT

Phone: 866.838.5052 704.909.5229

Email: TechSupport@SnapAV.com

HOW TO DISCOVER

- 1. Load the current version of Composer.
- 2. After Composer is loaded, browse to the Discover tab on the upper right-hand side of the screen.

NOTE: Auto-discovered devices appear in this section using SDDP protocol.

	Devices discovered via				- 🗆 X
Properties	SDDP	Items			
Properties			Discove	ared My Dr	vers Search
View External Documentation	^	Туре	Manufacturer	Model	Address
Product Info:		Receiver	Pioneer	SC-LX502	SC-LX502-PIONEER SC
	MolP	wattbox_wb70	WattBox	WB-700-IPV-12	WB700IPV12-D46A910
Controller Status: Online To edit the ZiaBee configuration, select the Project Name (New Project) ->	Controller	LIDevice	Luma Surveillance	C4-TSWMC7-EG	58 000FFF1701R9
Zigbee Server Configuration: Disabled Project Properties -> ZigBee Configuration tab.		Cable	Luma Surveillance	LUM-510-DVR 16CH	1E
Zinhee Server Status		A/V Switch	SnapAV	MoIP Controller	09
	1	Camera	Luma Surveillance	Luma-PTZ	PTZ_CAMERA-LUM-50
Zap Configuration Type: Disabled					
Zap Status: Not Running					
For Video Connection: Set Resolution Video Resolutions: 1280x720p @ 59.94/60Hz Current Resolution: 1280x720p @ 59.94/60Hz UO Firmware Version: 03.26.15 Advanced Audio: Custom Delay Stereo Audio Out 1 0 © ms					
Prioritize Coax Over HDMI					

- 3. Double click the discovered device to add it to the project.
- 4. See the screenshot below for an example of how successfully added devices appear in the project.

😮 Composer 2.10.1 - (Local)			
File Driver Go Tools Help			
System Design	Properties		Properties
System	Advanced Properties		Local IP
	Properties Actions Documentation	Lua	Address of the unit and
- Kew Project	Status	192.168.0.115 - Connected	connection
Device label	Controller Version	1.0.1.9	status.
Main After being added to the	Receivers	2	
Binary MoIP Controller Controller can be edited.	Transmitters	2	
▲ <u> </u>	Enable Automatic CEC Power Control	OFF	~
•	DEBUG MODE	OFF	~

MAKING THE CONNECTIONS

- 1. Bind the Tx and Rx to the source and display after the device has been added to the project.
- 2. Select Connections on the bottom left of the screen.
- 3. Bind the Tx first. Select Tx 1 and drag it to the HDMI Output Devices list at the bottom of the screen.

See example:

🤇 Composer 2.10.1 - (Local)						
File Driver Go Tools Help						
Connections	Control & Audio Video Connections			Select	the source,	
Control/AV Network	Binary MoIP Controller 2			and di	t HDML out	
	Name	Туре	Connection	d		
New Project	Audio/Video Inputs					
Home	🐨 TX 1	Video	HDMI	Input	XBOX One->HDMI Out	
House	🖶 TX 2	Video	HDMI	Input	Laptop PC->AV Out	
📥 🔁 Main	🖶 TX 3	Video	HDMI	Input		
🖨 🍋 Master	🗬 TX 4	Video	HDMI	Input		
	🗬 TX 5	Video	HDMI	Input		
- 🖉 Luma IP Camera	🖶 TX 6	Video	HDMI	Input		
- BunBrite TV IR Veranda 43/55/74	🗬 TX 7	Video	HDMI	Input		
XBOX One	🖶 TX 8	Video	HDMI	Input		
- Laptop PC	🗬 TX 9	Video	HDMI	Input		
Luma IP Camera P12	TX 10	Video	HDMI	Input		
Luma IP Camera 2	🖶 TX 11	Video	HDMI	Input		
Luma IP Camera Fisneye	🖶 TX 12	Video	HDMI	Input		
Digital Media	🖶 TX 13	Video	HDMI	Input		
	🗬 TX 14	Video	HDMI	Input		
- My Music	🗬 TX 15	Video	HDMI	Input		
My Movies	🗬 TX 16	Video	HDMI	Input		
- 🖬 Stations	🖶 TX 17	Video	HDMI	Input		
- Si Channels	🖶 TX 18	Video	HDMI	Input		
Binary MoIP Controller 2	TX 19	Video	HDMI	Input		
Luma IP Camera 3	TX 20	Video	HDMI	Input		
🗄 🜍 HouseLogix Test	TX 21	Video	HDMI	Input		
- Advanced Lighting	TX 22	Video	HDMI	Input		
	TX 23	Video	HDMI	Input		
	TX 24	Video	HDMI	Input		
	TX 25	Video	HDMI	Input		
	TX 26	Video	HDMI	Input		
	TX 27	Video	HDMI	Input		
	TX 28	Video	HDMI	Input	Bind the	Ixto
	TX 29	Video	HDMI	Input	the corr	rect
	TX 30	Video	HDMI	Input	sourc	e. 📐
	TX 31	Video	HDMI	Input		
	TX 32	Video	HDMI	Input		
	HDMI Output Devices		LISUL			-
	Device		Name		Location	Connections
					Master	Pinane MalP Controller 2 - TV 1
	Home Controller HC000		HDMI (Audio (Aideo)		Master	Binary Mole Controller 2->1X 1
	I anton PC				Master	Binary MoIP Controller 2-STX 2
System Design	HouseLogix PC and NVR	Control	Output		HouseLogix Test	binary moni Controlled 2-21X 2
Connections						

4. Bind the Rx next.

See example:

File Driver Go Tools Help						Select the correct		
Connections		Control & Audio Video Connections			Rx, and drag it to			
Control/AV	Network	Binary MoIP Controller 2			the correct			
	~ ~ ~ 6 9	Name	Туре	Connection	Input/Outp	uispiay input		
New Project		• 🍗 TX 48	Audio	STEREO	Input		.	
Home		Audio/Video Outputs						
House		RX 1	Video	HDMI	Output	SunBriteTV IR Veranda 43/55	5/74->INPUT 6 - HDMI 1	
🖻 📼 Main		🗬 RX 2	Video	HDMI	Output			
🖶 🎀 Master		🗬 RX 3	Video	HDMI	Output			
- G WB-700-IPV-12		🗬 RX 4	Video	HDMI	Output			
-/ Luma IP Camera		🗬 RX 5	Video	HDMI	Output			
- UR Vera	nda 43/55/74	🗬 RX 6	Video	HDMI	Output			
- XBOX One		🗬 RX 7	Video	HDMI	Output			
- Laptop PC		🐨 RX 8	Video	HDMI	Output			
-/Q Luma IP Camera P1	ΓZ	🐨 RX 9	Video	HDMI	Output			
/Q Luma IP Camera 2		🖶 RX 10	Video	HDMI	Output			
-YQ Luma IP Camera Fis	sheye	🐨 RX 11	Video	HDMI	Output			
Home Controller HC	800	🐨 RX 12	Video	HDMI	Output			
Digital Media		🐨 RX 13	Video	HDMI	Output			
Tuneln		🐨 RX 14	Video	HDMI	Output			
My Music		🗬 RX 15	Video	HDMI	Output			
My Movies		🗬 RX 16	Video	HDMI	Output			
Stations		BX 17	Video	HDMI	Output			
Channels		BX 18	Video	HDMI	Output			
Binary MolP Control	lier 2	BX 19	Video	HDMI	Output			
Heusel asix Test		BX 20	Video	HDMI	Output			
HouseLogix Test		BX 21	Video	HDMI	Output			
Advanced Lighting		BX 22	Video	HDMI	Output			
		BX 22	Video	HDMI	Output			
		E RY 24	Video	ПОМІ	Output			
		PX 25	Video	LDMI	Output			
		PX 25	Video	HDMI	Output			
		DX 27	Video	LDMI	Output			
			Video		Output			
		T DX 20	Video	HDMI	Output			
		- RX 29	Video	HDMI	Output	Bind the Rx to the		
		WRX 30	Video	HDMI	Output	correct display		
		RX 31	Video	HDMI	Output	input		
		HDMI Input Devices						
		Device		Name		Location	Copyrations	
		XBOX One		HMDI In		Master		
		SunBrite TV IR Veranda 4	3/55/74	INPUT 6 - HDMI 1		Master	Binary MoIP Controller 2->RX 1	
		SunBrite TV IR Veranda 4	3/55/74	INPUT 8 - HDMI 3		Master		
System Design		SunBrite TV IR Veranda 4	3/55/74	INPUT 9 - HDMI 4		Master		

FINISHING UP

1. Refresh the Composer and Navigators once all transmitters have been bound.

See example:

