

Partner: SnapAV  
 Model: Luma IP Camera  
 Device Type: Streaming



**GENERAL INFORMATION**

<b>SIMPLWINDOWS NAME:</b>	Luma IP Camera
<b>CATEGORY:</b>	Cameras
<b>VERSION:</b>	V1.0 – Original Release
<b>SUMMARY:</b>	This module controls a Luma IP Camera via TCP Connection.
<b>GENERAL NOTES:</b>	This module was designed and tested with a LUM-700-BUL-IPH-WH IP Camera. This module integrates a Luma IP Camera stream, as well as motion detection and input triggering. Motion detection and input triggering can be enabled and disabled independently.
<b>CRESTRON HARDWARE REQUIRED:</b>	3 Series processor
<b>SETUP OF CRESTRON HARDWARE:</b>	None
<b>VENDOR FIRMWARE:</b>	V5.3.6 build 160622
<b>VENDOR SETUP:</b>	Luma IP Camera module parameters must be entered before continuing. Refer to parameters section for descriptions. In screen designer, the URL must be set in the properties tab for whichever device the video stream will be on. Replace the below IP Address with the one of the IP Camera. The IP Address can be found through SnapAV's IP Utility Tool. <u>URL PATH EXAMPLES</u> MJPEG: http://192.168.24.172:80/wps-cgi/video.cgi?camera=1&StreamNum=1&resolution=640x360&format=MPEG&username=admin&password=admin JPEG: http://192.168.24.172:80/wps-cgi/image.cgi?camera=1&StreamNum=1&resolution=640x360&username=admin&password=admin
<b>CABLE DIAGRAM:</b>	

**Partner: SnapAV**  
**Model: Luma IP Camera**  
**Device Type: Streaming**


**CONTROL:**

MOTIONSTART	D	Starts the Motion Detection Events
MOTIONSTOP	D	Stop the Motion Detection Events
INPUTSTART	D	Starts the Input Trigger Events
INPUTSTOP	D	Stops the Input Trigger Events

**FEEDBACK:**

H264	A	Analog join for the embedded object h264 video source analog join. Must be used for video stream to display.
mjpeg	A	Analog join for the embedded object mjpeg video source analog join. Must be used for video stream to display.
URLImage	S	The path of the video stream for dynamic graphics just in case the default path is not specified. This path is only valid when used with the indirect graphics path serial join feedback.
URLVideo	S	The path of the video stream for motion jpeg just in case the default path is not specified. This path is only valid when used with the indirect graphics path serial join feedback.
motion	D	Output that goes high for 5 seconds when motion is detected. Motion detection event must be turned on.
input	D	Output that goes high when the camera's Input Trigger is open and goes low when it is closed.
URLh264Mainstream	S	The path of the h264 main stream
URLh264Substream	S	The path of the h264 sub stream

**PARAMETER:**

Device_ip\$	S	IP Address of the Luma IP Camera
Username\$	S	Username for authentication [Default: admin]
Password\$	S	Password for authentication [Default: admin]
Controller_ip\$	S	IP Address of the Crestron Controller

**Partner: SnapAV**  
**Model: Luma IP Camera**  
**Device Type: Streaming**



Camera_num\$	S	The number of the camera to be streamed, default = 1
Stream_num\$	S	The number of the stream, main = 1 and sub = 2
http_port	S	Port for HTTP Connection
H264_port	S	Port for h264 Connection
Listening_port	S	Port for the Crestron Controller to listen for events on. Should be different for each camera.

## TESTING:

OPS USED FOR TESTING:	RMC3 1.010.0060
SIMPL WINDOWS USED FOR TESTING:	4.03.24.00
DEVICE DB USED FOR TESTING:	77.00.004.00
CRES DB USED FOR TESTING:	58.00.002.00
SYMBOL LIBRARY USED FOR TESTING:	1006
SAMPLE PROGRAM:	Luma IP Camera Demo
REVISION HISTORY:	V1.0 – Original Release