



Alarm.com Smart Chime Data Sheet

ADC-W115C

www.alarm.com

© 2021 Alarm.com. All rights reserved. 210107

Specifications

Wi-Fi Connection: 802.11 b/g/n, 2.4 GHz

Wi-Fi Security: WPA2

LED Indicators: 4

Buttons: WPS, Reset

Antennas: 2 Wi-Fi

Chime: 1.5 W speaker, 77 dB

Operating Temperature: 32°F to 104°F
(0°C to 40°C)

Operating Humidity: 10% to 90%
(non-condensing) RH

Dimensions (H x W x D): With antennas 5.0 x
1.0 x 2.1" (12.7 x 13.0 x 5.4 cm)

Without antennas 3.3 x 3.3 x 2.1" (8.5 x 8.5 x
5.4 cm)



Overview

Designed to work seamlessly with the Alarm.com platform, the ADC-W115C serves as a robust Wi-Fi extender and customizable wireless doorbell chime. Add the Alarm.com Smart Chime to an account when an in-home chime is not a feasible option during a doorbell camera installation. Simply plug the ADC-W115C into a wall outlet, pair with the existing router, add a doorbell camera, and enjoy boosted network signals that provide instantaneous chime notifications.

Features

- Wireless doorbell chime
- Wi-Fi extender (2.4 GHz)
- Adjustable chime volume
- Customizable tones
- Simple, plug-in installation
- Remote management and troubleshooting

In the Box

- ADC-W115C Alarm.com Smart Chime
- Installation Guide

LED Guide

🔌	☁️	📶	🔄	🔌☁️📶🔄
On Device powered on	On Connected to Internet	On Device connected to chime	Off WPS mode not enabled	Blinking (escalating) Firmware upgrade in progress
Off Device powered off	Off No local or Internet connection	Off No device connected to chime	Blinking (slowly) WPS mode enabled to connect to router	Blinking (simultaneously) Reset in progress
Blinking Device booting up	Blinking Local connection, no Internet connection	Blinking (3 quick blinks) New device connected to chime	Blinking (rapidly) WPS mode enabled to connect to device	
	Blinking (5 quick blinks) Communication test initiated			