Motion Sensor



OVERVIEW

The Axxess Wireless Motion Sensor supports all motion dependent functions, including lighting, security, occupancy detection and energy management.

Upon detecting people moving in a space, it communicates that event wirelessly on a programmed schedule. It also measures temperature and light.

Utilizing a ball mount, the Wireless Motion Sensor is able to be adjusted to whatever direction you wish and enables quick removal.

The Wireless Motion Sensor can be combined with our Wireless Contact Switch to reliably determine occupancy status of a room. This is vital information for a variety of systems, including energy management, helping our environment while improving your bottom line.

Fully compatible with Control4.





Other products and company names mentioned in this document may be the trademarks or registered trademarks of their respective owners.

Motion Sensor

MS-C4ZB-R2

USES
- Energy management
- Security systems
- Automatic lights
- Home & office automation

WIRELESS
ZigBee PRO Compatible (802.15.4)

Control4 Driver Downloadable

COMPLIANCE/APPROVALS
FCC Part 15 | CE

LIGHT SENSOR
Detects levels from light to dark

POWER & BATTERY
- 2 - 1.5V AA alkaline/lithium batteries
- Low battery notification
- Over two year battery life

MOTION SENSOR
- PIR motion sensor (dual element ambient effect reduction)
- Viewing Angle: 90° H, 30° V
- Effective range: 30'

TEMPERATURE SENSOR
Accurate to +/- 1°C Operating range of -40°C to 70°C

DIMENSIONS
W 2.3" x H 3.03" x D 0.5"
W 5.84cm x H 7.7cm x D 1.27cm

COLORS
White | Black

DRIVERS
Download from www.axxind.com/dealers/drivers

HOW TO ORDER
axxind.com/dealers

POPULAR APPLICATIONS
Lighting / energy management
Occupancy detection
Security

WHAT'S IN THE BOX



Other products and company names mentioned in this document may be the trademarks or registered trademarks of their respective owners.