



## Specifications

Model	150A	300A	500A
Continuous Power Output (All Ch.)	150w per channel @70V	300w per channel @70V	500w per channel @70V
Inputs per Channel	1 unbalanced (set-screw) and 1 balanced (RCA)		
Input Sensitivity	700mV		
Input Impedance	10K $\Omega$ / Unbalanced, 20K $\Omega$ / Balanced		
AUTO ON (Audio Sense) Sensitivity	2.5mV		
12V Trigger Input	4.5 -12V DC; 10K $\Omega$		
12V Trigger Output	12V DC; 10mA		
T.H.D.	0.03%		
S/N ratio	95db A-weighted		
Frequency Response	50 Hz to 20 KHz		
Distortion	0.1% THD 20 Hz-20 KHz		
Input Voltage	115V AC / 230V AC		
Fuse for 115V AC	T4AL 250V	T8AL 250V	T10AL 250V
Fuse for 230V AC	T2.5AL 250V	T4AL 250V	T5AL 250V
Power Consumption	400 watts	800 watts	1200 watts
Dimensions (In.)	17" W x 2.3" H x 11" D		
Weight	7.8 lbs.	8.1 lbs.	8.4 lbs.
Certification	Meets FCC Part 15, UL EN60065		

## Real Performance for the Real World

These efficient Class-D 70V amplifiers are perfect for providing music in large outdoor spaces and areas that have different listening zones. They deliver gobs of power in a 2-channel design that's 50% slimmer than the competition, while running cooler and operating almost silently.

## Powerful Performance

Digital amplification allows these amps to provide impressive performance, while running 80% cooler than the competition - making them a powerful yet energy-efficient choice.

## Smart Features

With three convenient turn-on modes these amplifiers can be configured to work just about any way the application requires. Plus they integrate easily with simple volume controls or sophisticated control systems.

## Safe, Quiet Operation

Episode amplifiers are equipped with built-in ESD and surge protection to keep operating even in tough conditions. Gain control prevents clipping that could damage the amp or connected speakers, and a fanless design offers nearly silent performance.

## 2-Year Limited Warranty

*This Episode<sup>®</sup> Amplifier has a 2-Year Limited Warranty. This warranty includes parts and labor repairs on all components found to be defective in material or workmanship under normal conditions of use. This warranty shall not apply to products which have been abused, modified or disassembled. Products to be repaired under this warranty must be returned to SnapAV or a designated service center with prior notification and an assigned return authorization number (RA).*