

Amplifier Firmware Update Guide

Use the following procedure to update the firmware on your Mirage Audio System amplifiers - M-801e, M-401e, M-120e. Settings will NOT be erased. Please leave the amplifiers connected to the network.

Requirement: A computer with a Telnet client installed.

1. Connect to the amplifier via Telnet over port 17056.

TELNET <amp ip> 17056

NOTE: If Telnet is not available on your PC, follow the steps below to install it.

To install Telnet Server on Windows 7 and Windows Vista:

- Click **Start**, and then click **Control Panel**.
- On the **Control Panel Home** page, click **Programs**.
- Under the section titled **Programs and Features**, click **Turn Windows features on or off**.
- If the **User Account Control** dialog box appears, confirm that the action displayed is correct, and then click **Continue**.
- In the **Windows Features** list, select **Telnet Server**, and then click **OK**.

To install Telnet Server on Windows 10

- Click **the Cortana Search Function** and search **Turn Windows features on or off**.
- The **Windows Features** dialog box appears, scroll down to Telnet **Client**, check the box, then click **OK**.

2. Run the appropriate update commands, pertaining to the model you are updating.

INSTALL_BUNDLE updates.autonomic-controls.com/amp/Autonomic_M801e_release.bun

INSTALL_BUNDLE updates.autonomic-controls.com/amp/Autonomic_M401e_release.bun

INSTALL_BUNDLE updates.autonomic-controls.com/amp/Autonomic_M120e_release.bun

DO NOT POWER DOWN THE AMPLIFIER DURING THE UPDATE.

Reported progress will be displayed during the update process. When complete, the amplifier will reboot and the telnet client will close automatically.

NOTE: It is recommended that all amplifiers in a system run the same firmware.