



Powerful Sound, Impressive Versatility.

Episode 70V Mixer-Amplifier

Give your space the sound it deserves with the Episode 70V Mixer-Amplifier. It supports 50V, 70V, and 100V, as well as low impedance 4-ohm systems, and handles large commercial spaces with ease.



ECA-70MIXAMP-1-60



ECA-70MIXAMP-1-120



ECA-70MIXAMP-1-240

Multiple Inputs

With eight inputs, you can connect multiple microphones and analog sources. The integrated mixer blends the mic with any of the music sources, making it perfect for background music and paging applications.

Priority Mic Inputs

Balanced microphone inputs feature independent priority modes that enable audio "ducking," a feature that automatically reduces the music volume when the priority microphone(s) are being used.

Front Panel Controls

Need to make a few quick sound tweaks? You get easy access to Volume, Bass, Treble, Source Inputs and Mic level controls right from the front panel.

Episode 70V Mixer-Amplifier

	ECA-70MIXAMP-1-60	ECA-70MIXAMP-1-120	ECA-70MIXAMP-1-240
Power Output @ 4-ohms	60W	120W	240W
THD	<0.5%	<0.1%	<0.1%
Frequency Response [Hz]	50 - 16,000	70-16,000	70-16,000
Signal to Noise Ratio	73dB	68dB	73dB
XLR Inputs	2	4	4
XLR Pre-Out	No	1	1
1/4" Mic Inputs	2	0	0
RCA Inputs	2	4	4
Line Output	1	1	1
Audio Ducking	Yes	Yes	Yes
Dimensions	16.9" x 3.75" x 15.2"	16.9" x 3.75" x 15.2"	16.9" x 3.75" x 15.2"
Power Consumption	120W	160W	480W
Weight	15.7 lbs	24 lbs	36.4 lbs
Fan Cooled	Yes	Yes	Yes
Rack Spacing	2U	2U	2U
Emergency input	Yes	No	No