



## ClareOne Panic Pendant (Keyfob)

CLR-C1-PNC



### Specifications

Compatible panel	ClareOne (CLR-C1-PNL1)
Transmitter frequency	433MHz
Encrypted	Yes
Transmitted indications	Low battery
Visual indications	LED light
Battery type	CR2032
Operating temperature	32 to 120°F (0 to 49°C)
Relative humidity	95% non-condensing
Dimensions	2.25 x 1.25 in (57.15 x 32.75 mm)
Water resistant	No
Certifications	FCC: 15.109 Class B 15.231, Industry Canada: ICES-003, RSS-210, ETL listed to UL-1023 and ULC-C1023

The ClareOne Panic Pendant (Keyfob) is a wireless hand-held device that can be used as a portable panic button or life-safety device. The pendant features powerful, exceptional range and has a long lasting battery.

\*The ClareOne Panic Pendant must be within range of the ClareOne panel to function properly.

- Can easily send a signal to the ClareOne panel and to the central station for assistance
- Silicone, non-slip button is easy to find in the dark
- Signal on; push/push
- LED activates when panic signal has been sent
- Pairs easily and quickly with the ClareOne panel

By making home technology simple, Clare provides exclusive benefits to integrators, builders, and homeowners. We offer innovative home automation solutions, wireless security, controllable lighting, and IP CCTV components. For more information, visit [clarecontrols.com](http://clarecontrols.com).