
Wall SMART	Model: WS NC FOR C4 LUX 4 GANG DEVICES C4-L-	Family: WALL-SMART	
		DWG NO. 007-4NA36-SPC	
	Model No.: 007-1NA36	PRODUCT SPEC.	REVISION B DATE 05/Jun./2024

Make Your Wall Smart


"WS NC FOR C4 LUX 4 GANG DEVICES C4-L-" - Product description:


The "WS NC FOR C4 LUX 4 GANG DEVICES C4-L-" is a wall adapter for in-wall flush installation of C4 LUX 4 gang faceplate and C4-L-XX devices. The "WS NC FOR C4 LUX 4 GANG DEVICES C4-L-" firmly mounts the C4 LUX 4 gang faceplate and C4-L-XX devices while allowing easy insertion, removal and operation.



Key features and benefits:


- Flush with the wall.
- Paintable with the wall paint in any color and texture.
- Includes depth calibration mechanism
- Allows easy insertion and removal of C4 LUX 4 gang faceplate and C4-L-XX devices.
- The adapter is supplied unpainted (To be painted after installation as part of the wall).
- Designed to be installed in ½" drywall. Installation of the Wall-Smart adapter is straight-forward. Installation process is similar to drywall construction procedures. Before installation, read Wall-Smart installation instruction 10-04-00101-INS in http://www.wall smart.com/faq
- Designed for the use of C4 LUX 4 gang faceplate and C4-L-XX devices (C4 LUX 4 gang faceplate and C4-L-XX devices are not included).
- Adapter kit contains:
    1. Wall adapter (X1)
    2. KA3.5X8 Screws (X16)





Key properties:

- Dimensions: (W/H/D): 306.88mm (12.08")/ 203.2mm (8")/ 44 (1.73")
- Power Supply: None (manual adapter).
- Weight: 0.5Kg, 1.1lbs.
- Material: Moisture resistant MDF (compliant with TSCA Title VI)



INFORMATION CONTAINED HEREIN IS PROPRIETARY AND MAY NOT BE USED, REPRODUCED OR COPIED WITHOUT WRITTEN CONSENT OF WALL-SMART ©

Phone: (201) 205-2056 / info@wall-smart.com