

# PIR MOTION SENSOR

## 319.5MHZ, PET IMMUNITY

**ADI**  
**PRO**

With uncompromised detection capabilities and pet immunity processing up to 85 lbs., this motion detector offers reliable, false alarm free protection. Compatible with Interlogix, GE and Qolsys panels and receivers.



## FEATURES

Smooth rounded front finish mounts easily to walls or corners and blends easily with any interior

Engineered with innovative hidden Fresnel lens with wide, 40' x 40', 90° coverage pattern

Improved pet immunity up to 85 lbs.

Adjustable sensitivity levels – normal and high

Up to 5-year battery life, CR123A replaceable lithium battery

FCC and IC approved

2-year warranty

## 0E-PIR319V2

### Product Specifications

**PART#:** 0E-PIR319V2

**UPC:** 840049313149

**Dimensions:** 3.54" x 2.64" x 1.72"  
(90 x 67 x 43.6mm)

**Wireless Range:** Up to 500' (152.4m)

**Coverage Area:** 40' x 40'  
(12.2 x 12.2m), 90° angle

**Pet Immunity:** Up to 85 lbs. (38.56kg)

**Battery:** 3V lithium CR123A

**Operating Temperature:** 32° to 120°F  
(0° to 49°C)

**Compatibility:** 319.5MHz wireless protocol (encrypted formats excluded)



For more information, contact your ADI salesperson or visit [adiglobal.com/adiexclusivebrands](http://adiglobal.com/adiexclusivebrands)