

ADVANCED MUSIC BRIDGE

Quick Start Guide

The Advanced Music Bridge works with eSeries Mirage Media Servers to bring next generation features available in Mirage OS 7.0. Seamlessly add the AMB to any new or existing eSeries system with plug-and-play operation.



Backwards compatible with all eSeries Mirage Media Servers



Unlocks next generation features in Mirage OS 7.0



Access to two network streams of Apple Music



Adds Calm Radio music service

Full browse with control system

interfaces



Increased track limit to support large library systems



Plug & Play setup with new and existing eSeries systems



No audio interconnects needed between AMB and MMS



Setup Instructions

Step 1: Connect power and network to the AMB

Step 2: Visit the Firmware tab on the MMS

Configuration page or access the Autonomic Dealer Zone to verify/update the MMS firmware to Mirage OS 6.4 or later

Machine	System	Content	Schedule	Control Systems	Firmware	∉SERIES
↑ Firm	ware					
Current firmware	6.4.2022	20318.1				

Enter the MMS IP Address/config to access the MMS Configuration page when on the same network as the MMS (Ex. 192.168.1.2/config)

Step 3: Click "Add System Component" on the System tab of the MMS Configuration page and select the AMB

This will happen automatically if the MMS is on System ID "1"

,	'				2			-	
/lirage Audio System		Machine S	ystem	Content	Schedule	Control Syst	ems Firm	ware	es
	An Advance system to M Upgrade	ed Music Bridge Airage OS 7?	has been o	detected o	n the netwo	rk. Would you l	ike to upgra	de this	
	System	_						_	1
	System	ld 3 select Add sys	ed tem compo	nent]				
	Cle: Queue	ar ?	OFF						
	Clear Queu Lock	e Unlock (Clear Queue	Setting					
	Streamers								
	Model	Name [click	lo edit]	MAC		Outputs	Status		
	MMS-3e	MMS-3e		D46A	91622279	3	ок	1	
	Amplifiers								
	Model	Name [click to	edit]	MAC		Inputs / Zones	Status		
	M-801e	M-801e		D46A914	2006C	12 / 1 - 8	ОК	1	
	Additional	Devices							
	Model	Name	,	MAC		Outputs	Status		
	AMB	90e2fcb2ca09	ş	0e2fcb2ci	109	2	ок	20	

Stand Component

lodel	MAC	IP	System Id
AMB	90e21	10.10.1.173	1

Step 4: When prompted at the top of the page, click "Upgrade" to update the system to Mirage OS 7.0. This will prompt the MMS to restart.

An Advanced Music Bridge has been detected on the network. Would you like to upgrade this system to Mirage OS 7?

Step 5: After the MMS restarts navigate to the Content tab of the MMS Configuration page to add account information for Mirage OS 7.0 or greater supported streaming services.

Audio System		Content Sched			øSERIES
	Online Credentials			0	
	PANDORA			0 0-	
	demo@autonomic-controls.com	n	Connecte	d 오 📝 📋	
	SOUNDMICHINE			0-	
	Autonomic (development@au	tonomic-controls.com)	Connecte	d 오 🖌 🖻	
	Spotify			0 0-	
	autonomic		Connecte	d 오 🖌 😫	
	music			٥٠	
	É Music			0 0+	
	CALMRADIO			٥.	
	DEEZER			0+	
	iHeartRADIO			0 0-	
	220422.2				



Note: At least one eSeries MMS is required for operation with the AMB. Each AMB supports two streams of Apple Music. Learn more about setup and installation at **Autonomic.biz/support** and visit the **Autonomic Knowledge Base**.



Questions? +1 914 598+1647 or sales@autonomic-controls.com @2006-2022 Autonomic Controls, Inc. 28 Kaysal Ct., Armonk NY 10504 06012022