

# MusicCast AV Receiver RX-A1080



# Architected for Performance

Constructed for performance, this 7.2-channel AV receiver features an ESS Sabre DAC, seven HDMI® inputs, three HDMI® outputs, Dolby Atmos® and DTS:XTM, Zone 2 function, phono input, Wi-Fi®, YPAOTM with precision EQ and much more.







**M**usicCast















**6** 















Bluetooth





























- 7-channel powerful surround sound 110 W per channel (8 ohms, 20 Hz-20 kHz, 0.06% THD, 2-ch driven) 135 W per channel (8 ohms, 1 kHz, 0.9% THD, 2-ch driven) 170 W per channel (6 ohms, 1 kHz, 10% THD, 1-ch driven) (JEITA)
- H-shape cross member frame
- Symmetrical power amplifier layout
- Heat sink with anti-vibration and anti-thermal properties
- Professional grade ESS 384 kHz / 32-bit SABRE™ DAC (ES9007S) NEW
- High-speed thermal feedback power amplifier
- High-quality volume IC and independent pure power supply
- Ultra low-iitter PLL circuitry helps optimize sound imaging
- Highly rigid construction including Anti-Resonance Technology (A.R.T. Wedge) to reduce
- · Advanced design feet enhance strength and vibration resistance
- High-resolution Music Enhancer further heightens musicality from the original content
- Compressed Music Enhancer for Bluetooth<sup>®</sup>
- Phono input for vinyl playback

## Video Features

- Latest HDMI® (7 in / 3 out) with 4K Ultra HD Full Support (4K / 60p [4:4:4]), HDR video, Hybrid Log-Gamma and Dolby Vision Compatibility and BT.2020 pass-through
- 4K video upscaling from analog and HDMI input
- Yamaha original video processing that optimizes processing for each type of video content
  - Motion-adaptive and edge-adaptive deinterlacing
- Multicadence (including 3-2 pull-down) detection
- Resolution enhancement (detail and edge enhancement)

## Advanced Features

- Ability to add MusicCast Surround speaker(s) (MusicCast 20 or MusicCast 50)
   NEW
- Amazon Alexa voice control compatibility NEW Ability to add wireless subwoofer (MusicCast SUB 100) NEW
- MusicCast for audio enjoyment in every room
- Bluetooth for wireless music streaming (SBC / AAC)
- Network functions Wi-Fi built-in (802.11b / g / n, 2.4 / 5 GHz)
  - Easy Wi-Fi setup, i.e., iOS Wi-Fi settings sharing, WPS etc.
- AirPlay allows music streaming from Mac, PC, iPod®, iPhone®, iPad®
- AV Controller app for operating various functions from iOS or Android™ smartphones and tablets
- Access to internet radio (airable radio), MP3, WMA, streaming services (Spotify, Napster,
- Pandora®, SiriusXM, SiriusXM Music for Business, TIDAL, Deezer)
  Music files on PC / MP3 / WMA / MPEG-4 AAC: up to 48 kHz / 16-bit, ALAC: up to 96 kHz / 24-bit, FLAC: up to 192 kHz / 24-bit, WAV / AIFF: up to 192 kHz / 32-bit, DSD: up to 11.2 MHz **NEW**
- Triggered auto playback with MusicCast devices

- · Gapless playback compatibility allows play without interruption
- · Front panel USB digital connection for USB thumb drives
- Advanced GUI on-screen display with HD capability NEW YPAO™- R.S.C. sound optimization with precision EQ calculation with multipoint
- measurement
- · High-sensitivity YPAO microphone for more precise measurement
- SCENE PLUS- simple and versatile functionality
   8 SCENE choices (4 on front panel and others on remote control) NEW
  - Zone SCENE- 4 SCENE buttons for Zone 2
- HDMI CEC powers up compatible TVs and Blu-ray Disc™ players
- Versatile parameters can be stored into each SCENE

## Surround Realism

- Surround:Al automatically optimizes the surround effect in real time
   Dolby Atmos® and DTS:X™ with CINEMA DSP HD³
- Enhanced CINEMA DSP program (total 24 DSP programs)
- Rear presence channel support for maximum 3D sound effect
- Compressed Music Enhancer with CINEMA DSP
- Dialogue Lift ensures that dialogue comes from the center of the screen
- Dialogue Level Adjustment for proper sound balance with dialogue and vocals
   Virtual Presence Speaker function for CINEMA DSP HD<sup>3</sup> surround without front presence
- Virtual Surround Back Speaker for playing 7.1-channel content with a 5.1-channel system
- YPAO™ Volume to ensure natural sounds even at low volume
- Extra Bass enriches the powerful bass sound even with small speakers
- SILENT CINEMA™ to enjoy surround sound with headphones

## Versatile Zone Control

- Pre out terminal for Zone 2 with volume control
- Advanced HDMI Zone Switching allows various input sources to be output via HDMI and enjoyed in different rooms
- Zone Extra Bass for more powerful bass sound in another room (Zone 2)
- Zone Volume Equalizer for optimum sound balance in another room (Zone 2)
- · Zone 2 on / off and control on front panel
- System backup / recovery function
- Zone mono, Zone volume, Zone tone controls, Zone balance, Zone audio delay and Party

## Eco-Friendly Design

- ECO mode operation for about 20%\* less power consumption
   \*Compared to power consumption when ECO mode is off (Yamaha measurement)
- Auto Power Standby function with variable time setting
- With an advanced energy saving design, this AV receiver achieves a low power consumption of not more than 2 W when in Network Standby mode.

## Surround:AI

The AI technology built into the DSP instantaneously analyzes each scene by focusing on distinct sound elements such as dialogue, background music, ambient sounds and sound effects, and automatically optimizes the surround effect in real time. This creates a compelling sense of realism, giving you the most profound entertainment experience possible.



#### Professional Grade

Incorporating the 32-bit SABRE™ ES9007S DAC from ESS Technology to achieve an exceptionally good signal-to-noise ratio and up to 120 dB of dynamic range, this AV receiver produces professional quality digital audio.



## Professional-Grade Sound Optimization

YPAO™ - Reflected Sound Control analyzes room acoustics and measures various speaker characteristics, then calibrates audio parameters to achieve optimum sound at any of eight listening positions. It uses precision EQ calculation and Reflected Sound Control to correct early reflections for studio-quality sound.



7.2
110 W
135 W
170 W
135 / 165 / 210 / 280 W

General	
Standby Power Consumption (IR only)	≤ 0.1 W
Auto Power Standby	Yes
ECO Mode	Yes
Dimensions (W x H x D)	17-1/8" x 7-1/8" x 17-1/4"
	(with antenna up: 17-1/8" x 10-1/4" x 17-1/4"
Weight	32.8 lbs.



#### **Extensive Connections**

7
1/1
1 (front)
1/1
3
3
9 (1 front)
2
4

Outputs	
HDMI (HDCP 2.2)	3 (Main, Zone B, Zone 2)
Pre Out	7.2-ch
Speaker*2/*3	7-ch / 9 ter
Subwoofer	Mono x 2 or stereo or front and rear
Headphone Jack*1	1 (front)

Zone 2 Audio Out	2
Remote In/Out	1/1
+12V / Total 0.1A Trigger Out	2
RS-232C	1
Terminal for Detachable Power Cable	1

• AirPlay works with iPhone, iPad, and iPod touch with iOS 4.3.3 or later, Mac with OS X Mountain Lion or later, and Mac and PC with Tunes 10.2.2 or later Supports iOS 7 or later for setup using Wireless Accessory Configuration. Apple is not responsible for the operation of this device or its compliance with safety and regulatory standards. Please note that the use of this accessory with iPod, iPhone, or iPad may affect wireless performance. AirPlay is a trademark of Apple Inc., registered in the U.S. and other countries. • The Bluetooth\* word mark and logos are registered trademarks owned by Bluetooth SIG, inc. and any use of such marks by Yamaha Corporation is under license. Other trademarks and trade names are those of their respective owners. • The Wi-FI CERTIFIED Logo is a certification mark of the Wi-FI Alliance. "Wi-FI and "Wi-FI Protected Setup" are marks or registered armale marks of the Wi-FI Alliance. "Wi-FI and "Wi-FI Protected Setup" are marks or or registered armale marks of the Wi-FI Alliance. "Wi-FI and "Wi-FI Protected Setup identifier Mark is a mark of the Wi-FI Alliance." Wi-FI and and "Wi-FI Protected Setup identifier Mark is a mark of the Wi-FI Alliance." Wi-FI and and "Wi-FI Protected Setup identifier Mark is a mark of the Wi-FI Alliance. The Wi-FI Protected Setup identifier Mark is a mark of the Wi-FI Alliance." Alliance and or the countries of the Wi-FI Alliance. The Wi-FI Alliance and trademarks of the Special Section of the Wi-FI Alliance and the Countries of the Wi-FI Alliance. The Wi-FI Alliance and the Countries and registered trademarks of District and the Special Section of the Wi-FI Alliance. The Wi-FI Alliance and the Countries of the Wi-FI Alliance and the Countries of the Wi-FI Alliance. The Wi-FI Alliance and the Countries of the Wi-FI Alliance and the Countries of the Wi-FI Alliance and the Wi-FI Alliance. The Wi-FI Alliance and the Countries and the Countries of the Wi-FI Alliance and the Countries and the Countries and the Wi-FI Alliance. The Wi-FI Alliance and the Countri



<sup>\*1</sup> Including front panel terminals \*2 Extra SP1 terminals are assignable to Front Presence, Zone 2 or bi-amp.

<sup>\*3</sup> Extra SP2 terminals are assignable to Surround Back or Zone 2.