



Visualint Touch

VI-TOUCH	Visualint Touch 7" Touch Panel
Power Requirement	9- 30vdc or PoE (15.4 Watts)
Network	10/100 Network Port
Maximum Users	128
Maximum Cameras	256
Maximum Groups	4
Maximum Number of Visualint Touch Panels Per Site	8
Number of Setting Logic Groups	1
Maximum Number of Events Controlled per Camera	Camera specific
Mounts Included	Flush Mount
Indoor/Outdoor	Indoor use only
Video Stream Control	Yes
Exit Delay	Selectable per group
Entry Delay	Only supported on VIM cameras
Monitoring Station Support	Sureview Immix
High Security Mode	<ul style="list-style-type: none"> - Optional supported features when selected - Each group must have an exit delay - Groups names and status will not be display until valid code is entered
Mounting Options	Surface Wall Mount In-Wall Mount

